
# 200 Watt Pulse Start Lamp







#### Vertical $\pm 15^{\circ}$



Dia. =	3.5" (90mm)
MOL =	8.3" (211mm)
LCL =	5.0" (127mm)
Base =	Mogul (EX39)

# MP 200W/V/PS/740 GENERAL Characteristics

Lamp Type	MH Pulse Start Single Ended
ANSI Code	M136/0
Bulb Shape	ED28
Base Type	Mogul (EX39)
Bulb Finish	Clear
Rated Life	20000 hours
Operating Position	Vertical ±15°

### **PHOTOMETRIC**

Initial Lumens	20000	
Lumens Per Watt	100	
Lamp Lumen Depreciation (LLD)	0.86 (86%) @ 8000	
Correlated Color Temperature	4000K	
Chromaticity Coordinates (CIE-x,y)	.385 .390	
Color Rendering Index (CRI) R <sub>a</sub>	68	

#### PHYSICAL

Bulb Diameter	3.5" (90mm)	
Max. Overall Length (MOL)	8.3" (211mm)	
Light Center Length (LCL)	5.0" (127mm)	
Effective Arc Length	23.6 mm	
Max. Base Temperature (°C)	210	
Max. Bulb Temperature (°C)	400	
Socket Pulse Rating (KV)	4	
Luminaire Type	Open / Enclosed Rated	

# ELECTRICAL

Lamp Watts	200
Lamp Oper. Voltage (Nom.)	132

ZZI4/ DATA SHEET

# SUSTAINABILITY


Mercury Amount (mg)	22.6
Picograms of Hg per Mean Lumen Hour	66

#### NOTES


- Lamp performance ratings published in this data sheet are based upon operation with approved electronic ballasts.
- Operation of position-rated lamps outside of their tolerances will result in poor performance.
- Minimum Starting Temperature: -40°C/°F.
- To calculate nighttime Scotopic lumens, multiply the lumen rating by the S/P ratio (1.7).

Complies with (CE), Low Voltage (CE), WEEE and RoHS Directives

Warning: This lamp can cause skin burn and eye inflammation from shortwave ultraviolet radiation if outer envelope of the lamp is broken or punctured. Do not use where people will remain for more than a few minutes unless adequate shielding or other safety precautions are used. Lamps that will automatically extinguish when outer envelope is broken or punctured are commercially available.



# Lumen Maintenance



#### Venture Lighting Australia

110 Lewis Road Wantirna South VIC 3152 Ph:+61 3 9800 5600 sales@venturelighting.com.au venturelighting.com.au

#### Venture Lighting New Zealand 8 Boeing Place Mount Maunganui Ph: +64 07 579 0163 light@adlt.co.nz

venturelighting.co.nz

#### Venture Lighting Singapore

Ph:+6568442338 sales@adlt.com.sg venturelighting.com.sg